

Headquarters Electrostart Bulgaria, 1404 Sofia 81, Bulgaria Blvd. Building 2, office 6, tel + 359 2 400 77 71 Fax + 359 2 400 77 84 email: info@electrostart.com www.electrostart.com

Surge Protective Device 10kV T3 for Class II LED drivers & Luminaires

LED SPD 10kVIIL T3

Features:

- \odot Wide range of mains supply AC voltage 100-277V&50/60Hz
- o Long life time & high durability
- o Suitable for insulation Class II luminaires, drivers, power supplies only
- High surge protection levels of up to 10kV/10kA
- For better surge protection of LED luminaires/drivers is recommended tandem use of T2 & T3 protectors
 - **Applications:**
- Highways lighting
- Rural roads lighting
- Industrial zones lighting

Protection

| Protection mode | Diff. mode | | |
|--|--|--|--|
| Type of surge protection device according IEC/EN 61643-11 | Т3 | | |
| Power grids | TNC, TNC-S, TNS, TT | | |
| Max. voltage protection level at In Up(L-N) | 1.8kV | | |
| Thermal protection | Yes | | |
| Maximum recommended overcurrent protection of protected by SPD line | 10A, gG fuse | | |
| Status indicator "end of life" | Yes, optical, ON: SPD is functional; Light OFF: SPD must be replaced | | |
| Suitable for luminaires of Safety Class | I | | |
| Ingress protection | IP20 | | |

Electrical characteristics

| Mains supply voltage Un(L-N) & Frequency | 100 277VAC & 50/60Hz | |
|--|----------------------------|--|
| Max. continuous operating voltage Uc(L-N) | 280VAC 50/60Hz | |
| Rated load current | 5A | |
| Power losses | 0.5W at Uc | |
| Temporary Overvoltage Ut (tt=5s; TN, TT-systems; LV system faults in consumer installation, 255VAC*1.32) | 337VAC | |
| Temporary Overvoltage Ut (tt=120min; TN, TT-systems; LV system faults in distribution system and loss of neutral, 255VAC* $\sqrt{3}$) | 442VAC | |
| Nominal discharge current In(L-N) | 5kA 8/20uS current wave | |
| Nominal discharge current In(L-GND) & In(N-GND) | 5kA 8/20uS current wave | |
| Open circuit voltage Uoc | 10kV 1.2/50uS voltage wave | |
| Max. voltage protection level at In Up(L-N) | 1.8kV ± 10% | |





 Headquarters

 Bulgaria, 1404 Sofia 81, Bulgaria Blvd. Building 2, office 6, tel + 359 2 400 77 71

 Fax + 359 2 400 77 84

 email: info@electrostart.com

 www.electrostart.com

Surge Protective Device 10kV T3 for Class II LED drivers & Luminaires

| Durability | | | |
|--|---|--|--|
| Surge withstand capability | 1 strike at 10kA max | | |
| | ≥ 20 strikes at 5kA max | | |
| | | | |
| Ambient conditions | | | |
| Allowable operating ambient temperature ta | -30 +70°C | | |
| Max. allowable casing temperature tc | +80°C | | |
| Storage & Relative humidity | -30 +80°C & 5 95% non-condensing | | |
| Suitable for outdoor luminaires | Yes, built-in usage only | | |
| Expose of UV radiaton and/or Sun light | Not allowable, do not expose | | |
| Air pressure and altitude | 80 106kPa & -500 +2000m | | |
| Connections | | | |
| Connections to mains supply network | 4 pole terminal block 0.5 2.5sq.mm | | |
| Connections to protected line & device | by terminal block 0.5 2.5sq.mm | | |
| Sizes&Fixing | | | |
| Dimensions | 77*34*30mm (only body) | | |
| Fixing screw type | M8x10 | | |
| Material | | | |
| Material of Body | plastic | | |
| Weight (incl nut) | 86 ± 3 g | | |
| Replacable parts | No replacable parts | | |
| Warranty conditions | | | |
| Lifespan at tc < 80°C | up to 100 000h in depends of strikes and Tc | | |
| Warranty | 5 Years and/or according strikes and Tc | | |
| | | | |
| Sertification | | | |
| CE | | | |
| Classification | Class III tests acc. EN61643-11 | | |
| Designation | Type 3 acc. EN61643-11 | | |
| | | | |
| Madified Data Pay | Description of Change | | |

| Modified Date Rev. | | Description of Change | | |
|--------------------|-----|-----------------------|------|----|
| | | ltem | From | То |
| 22.2.2024 | 1.2 | Datasheet Release | / | / |



Headquarters Bulgaria, 1404 Sofia 81, Bulgaria Blvd. Building 2, office 6, tel + 359 2 400 77 71 Fax + 359 2 400 77 84 email: info@electrostart.com www.electrostart.com

Surge Protective Device 10kV T3 for Class II LED drivers & Luminaires

Application diagram:

